











A1S

Center of Your Home Security

Internet Alarm Hub

A1S is a 100% wire-free Internet Alarm Hub that works with EZVIZ's smart sensors and security cameras in your house. Together, these security devices alert you to any abnormal events throughout the day and night. Thanks to its built-in rechargeable battery and optional cellular backup, the A1S will make sure your security system stays online and stays connected.

Key Features

-  Private Protocol Design
-  Works with up to 32 EZVIZ Sensors
-  Internet Connection via Wired, Wi-Fi and Cellular Network
-  Alerts via MSG, SMS, and Phone Call
-  Human Voice Alert
-  Built-in Backup Battery
-  Remote Control
-  Easy Installation



Your New, Custom-Made Smart Home

DIY your integrated smart home system with EZVIZ's many devices, all wireless and controllable via the EZVIZ App. A1S can connect up to 32 EZVIZ devices within a range of 150 meters (\approx 500 feet) so you can design your security net to provide the right amount of protection for your home.



Three Ways of Connection

We know you only have a limited number of Ethernet ports on your router, so we've added wireless connectivity to the A1S. In case of accidental Internet outages, A1S will automatically switch from Cable or Wi-Fi to the cellular backup, delivering non-stop protection. Remote control of the A1S and its connected devices remains effective using the cellular connection.

*A SIM card plus a data plan should be purchased from a local carrier.
Note that remote control may be disrupted on 2G connection.



SIM Card



Wi-Fi



Cable



Rechargeable Battery Backup, Just in Case

You can count on the built-in 4610 mAh battery of the A1S to provide uninterrupted security in the event of unexpected power outages.



Never Miss an Alert

Remote alerts have now gone pro with the A1S! In addition to app notifications, you will also receive alerts in the form of text messages and phone calls after inserting a SIM card -- no strings attached! Add a maximum of 3 emergency contacts on the EZVIZ App, and you are safe and sound.



Smarter Protection

Tell A1S you are away, at home, or sleeping on the EZVIZ App or via the EZVIZ Remote Control so it won't trigger stressful alarms when you're home, but it will continue to safeguard your house when you're away.



Specifications Model CS-A1S-32WE2G/3G/4G

Wireless Detector

Maximum	32(Optional)
Distance between detector and AIS	Max.150m(Open Space)
Detector Type	Wireless Open-close Detector/Wireless Pet Immune PIR Detector/Wireless Siren/Remote Controller etc.
Carrier Frequency	868MHz ; 433MHZ ; 868MHz/915 MHz
Transmission Power	10dBm

Network Features

Network Type	Ethernet Cable, Wi-Fi, 2G ; Ethernet Cable, Wi-Fi, 3G ; Ethernet Cable, Wi-Fi, 4G
Wi-Fi Pairing	AP Pairing

Function

Alarm Notification	EZVIZ app, SMS, Phone Call
Voice Prompt	Support human voice prompt and real-time alarm

Others

Power Voltage	DC 5V
Built-in Battery	Rechargeable Capacity: 4610mAh Standby: Time 10 hours
Power Consumption	≤5W
Product Dimensions	138×113×65 mm (5.4×4.5×2.6 inch)
Packaging Dimensions	213×143×84 mm (8.4×5.6×3.3 inch)
Weight	350g

Package Contents:

- A1S Internet Alarm Hub
- Device Base
- 1-meter (3.3-foot) USB Cable
- Power Adapter
- Drill Template
- Ejection Pin
- Screw Kit
- Quick Start Guide

Certificates

UL / FCC / REACH SVHC / WEEE / CE / RoHS

Operating Environment:

- Temperature: -10 - 45°C (14 - 113°F)
- Humidity: 0%--95%(No condensing)

